

T8 Series Linear LED Tube

This T8 LED tube does not require a ballast to work and offer a built-in universal line voltage driver, making it a top-of-the-line.



For Replacement use, see user guide.



Code	Lamp Power(W)	PF	Luminous flux (lm@4000K)	CCT (K)	CRI	Lifetime (hrs)	Socket	Dimension (mm)	Beam Angle(°)
io-401028	9	> 0.9	900	3000/4000/6500	83	35000	G13	26x600	240
io-401029	18	> 0.9	1800	3000/4000/6500	83	35000	G13	26x1200	240
io-401030	24	> 0.9	2400	3000/4000/6500	83	35000	G13	26x1500	240

T5 Series Linear LED Tube

This T5 LED tube directly compatible electronic ballasts, fast for replacing fluorescent tubes as a more sustainable light source, quick and easy to install. No wires to replace, no hassle of changing drivers.



Code	Lamp Power(W)	System Power(W)	Ballast	Luminous flux (lm@4000K)	CCT (K)	CRI	Lifetime (hrs)	Socket	Dimension (mm)	Beam Angle(°)
io-401031	6	9	HE	870	3000/4000/6500	83	35000	G5	18.4*549	240
io-401032	10	13	HE	1250	3000/4000/6500	83	35000	G5	18.4*849	240
io-401033	13	16	HE	1550	3000/4000/6500	83	35000	G5	18.4*1149	240
io-401034	18	21	HE	2000	3000/4000/6500	83	35000	G5	18.4*1449	240
io-401035	12	15	HO	1450	3000/4000/6500	83	35000	G5	18.4*549	240
io-401036	21	24	HO	2300	3000/4000/6500	83	35000	G5	18.4*849	240
io-401037	29	32	HO	3100	3000/4000/6500	83	35000	G5	18.4*1149	240
io-401038	37	40	HO	3600	3000/4000/6500	83	35000	G5	18.4*1449	240