

CJB15 Series Electronic Sirens



- 6 tones contained: Air horn, Siren, Wail-1, Wail-2, Yelp, Hi-Lo.
- Powers from 80Watts, 100Watts, 150Watts, 200Watts, 300Watts to 400Watts are available to be selected.
- The siren with power of 150Watts, 200Watts, 300Watts, 400Watts has the ability to broadcast two tones at the same time when connecting with two speakers in two channels.
- With light control to match any version of lightbars supplied by Senken.
- Microphone has the priority, when push the microphone to talk, all siren functions would be stopped.
- Siren tones could be modified to make custom tones.



Model	CJB80-15S	CJB100-15S	CJB150-15S	CJB200-15S	CJB150-15	CJB200-15	CJB300-15	CJB400-15
L(mm)	168	168	168	168	240	240	240	240
W(mm)	156	156	156	156	156	156	156	156
H(mm)	55	55	55	55	55	55	55	55
General Current	7A ± 1A	8.5A ± 1A	11A ± 1A	15A ± 1A	13A ± 2A	15A ± 2A	22A ± 2A	30A ± 1A
Rated Voltage	DC12V	DC12V	DC12V	DC12V	DC12V	DC12V	DC12V	DC12V
Load Impedance	8 Ω	8 Ω	6 Ω	6 Ω	8 Ω+8 Ω	8 Ω+8 Ω	6 Ω+6 Ω	6 Ω+6 Ω
Audio Voltage	25V ± 1V	29V ± 1V	30V ± 1V	35V ± 1V	25V ± 1V	29V ± 1V	30V ± 1V	35V ± 1V
PA Voltage	≥ 18V	≥ 18V	≥ 18V	≥ 18V	≥ 18V	≥ 18V	≥ 18V	≥ 18V
Static Current	≈300mA	≈300mA	≈300mA	≈300mA	≈350mA	≈350mA	≈350mA	≈350mA
Idling Current	≈0.7A	≈0.7A	≈0.7A	≈0.7A	≈1A	≈1A	≈1A	≈1A