

4" Smart Switch Pro

Product Presentation

1. Exterior view



2. Product Main Features

- Compatible with Chinese standard wall boxes, simple in wall installation.
- 4-inch HD LCD, IPS, multi touch screen, Dual array microphone with noise reduction, Auto light sensor, built in 1W speaker.
- Android OS 8.1, Quad Core 1.8G, 2G RAM + 8G ROM, Built in WiFi, BLE 4.2, ZigBee 3.0, Ethernet, RS485.
- Smart Home voice control, ZigBee gateway function, APP remote control.
- Control the lights, curtains, air conditioners, and all other Smart Home devices.
- Configure Smart Home scenes in the APP, turn on the scene mode with one touch on the screen or easily voice control.

3. Specification

Product	4" Smart Switch Pro (ZigBee 3.0)		Remark
Body Size	Dimensions(mm)	86mm×86mm×10mm (without the base) 86mm×86mm×36.6mm (with the base)	
	Weight(g)	210g	
	Color	Black glass + Black plastic frame + Black case	
Screen	Type	Capacitive TP	
	TP Type	G+F 5 points	
	LCD	TFT	
	Size	4"	
	Resolution	480*480	
	Multitouch	5 points	
Sound	Speaker	1 W	
	Music play	Yes	
	Mic	Dual array microphone	
General	Power	AC 100-240V 50/60Hz	
	CPU	PX30 Quad Core Cortex- A35	
	OS	Android 8.1	
	Memory	2GB RAM + 8GB ROM	
	Light Sensor	YES	
	Proximity Sensor	No	
Communications	ZigBee	Tuya ZigBee 3.0	
	RS485	RS485	
	Bluetooth	BLE 4.2	
	WiFi	802.11b/g/n 150Mbps 2.4G	

Ports	Power	AC 100-240V 50/60Hz	
	Relay	2 relays	Load no more than 200W for each relay
	RS485	RS485	
	Ethernet port	10M/100M Self-adaptive fast ethernet	
Working conditions	Working temperature	0 - 40 degrees	
	Working humidity	5% - 90% RH	

4. Installation instructions

- Turn off the main power in the electricity box and confirm the fire wire is not alive with a test pencil.
- Remove the base of the Smart Switch and install it in the wall box (as shown in the pictures following).
- Check the wires and make sure the wires are in good contact with the terminals and no exposed cooper wires.
- Fasten the base to the wall box with mounting screws and fix the Smart Switch back to the base.
- Note that the screws should not be screwed too tight during installation, in case any deformation or damage to the screen and hardware.
- If the Smart Switch is not flat after installation, do not press the screen violently, please check the wall box and the base installation at first.
- Please note the product does not support POE power supply.
- The product must be installed by professional electricians. The product should be kept away from fire and water during installation and use.

