Folding Bluetooth keyboard
With Touchpad

User's Manual

Compatible System

We iOS /Android/Mac

Note: Please read the user manual carefully before you start using this product

Product introduction

Front

Back

● iOS Connection Instructions:

1.Please open the touchpad side power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2.Open the tablet PC setting "Bluetooth" into searching and pairing status.

3.You will find the "Bluetooth keyboard"and then click to next step.

4.There is a tip for connecting successfully, you can use your keyboard comfortably .

● Win 10 Connection Instructions:

1.Please open the touchpad side power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2. Open settings, turn on Bluetooth, click Add Bluetooth or other devices.

3.Select "Bluetooth" in the Add Device to search.

4. You will find the "Bluetooth keyboard" and then click the pairing name to connect.

5.There is a tip for connecting successfully, you can use your keyboard comfortably .

● Android Connection Instructions:

1.Please open the touchpad side power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2. Open "Settings" and then click "Connect"

3. Turn on Bluetooth to search for the pair name.

4. Click the pair name "Bluetooth keyboard", pair request in displayed, click OK.

5. There is a tip for connecting successfully, you can use your keyboard comfortably .

●MacOS connection instructions:

1.Please open the touchpad side power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2. Please open system preferences and click on Bluetooth.

3.Until the "Bluetooth keyboard" is found , Then click on the pairing connection.

4.There is a tip for connecting successfully , you can use your keyboard comfortably .

Remarks: After connecting successfully the next time you don't need match code, just open the Bluetooth keyboard power switch and the tablet PC "Bluetooth", The BT keyboard will search the device and automatic connect.

Product features

iOS/Android		Windows		Windows	
Fn+	Corresponding function	Fn+	Corresponding function	Fn+	Corresponding function
Ctrl	Return to Desk	Ctrl	Home Page	Ctrl	Esc
Ctrl	Search	Ctrl	Search	Ctrl	F1
Ctrl	Select	Ctrl	Select	Ctrl	F2
Ctrl	Copy	Ctrl	Copy	Ctrl	F3
Ctrl	Stick	Ctrl	Stick	Ctrl	F4
Ctrl	Cut	Ctrl	Cut	Ctrl	F5
Ctrl	Previous track	Ctrl	Previous track	Ctrl	F6
Ctrl	Play/Pause	Ctrl	Play/Pause	Ctrl	F7
Ctrl	Next track	Ctrl	Next track	Ctrl	F8
Ctrl	Mute	Ctrl	Mute	Ctrl	F9
Ctrl	Volume-	Ctrl	Volume-	Ctrl	F10
Ctrl	Volume+	Ctrl	Volume+	Ctrl	F11
Ctrl	lock	Ctrl	lock	Ctrl	F12

Three system input method switch

iOS/Mac: control+ Space key Windows : control+ Shift

Android : control+ Shift

Three system switching languages

iOS/Mac : control+Space key switch language

Windows : Alt+Shift switch language

Android : Shift+Space key switch language

Technical Specifications

Keyboard size: 304.09 x 97.79 x 6.1 mm (open) 152 x 100 x 20 mm (folding)

Touchpad size: 132.3 x 61 mm

Weight : 274 g

Key working current : < 4 mA

Standby current : < 0.65 mA

Touchpad working current : 18 mA

Sleep current : 27 μA

Working distance: 10 m

Sleep time : Ten minutes

Lithium battery capacity : 140 mAh

Awaken key : Press key

Working voltage: 3.7 V

Charger specifications: 5V ⎓ 1A or 2A

Status Display LED

- Connect : Open the power switch, blue lights up, press the connect button, blue light twinkles.
- Charging : Indicator light will be on green, after fully charging, the light crash out.
- Low Voltage Indication : When the voltage is below 3.3 V, red light twinkles.

Touchpad function description (Windows10), must be switched to Windows system

Touch pad function description (Android), must be switched to Android system

Touch pad function description (iOS 13.4.1 and above), must be switched to iOS system

User-defined:

Settings - Auxiliary Functions - Touch - Auxiliary Touches - Device - Click the keyboard's pairing name, and then Customize the function of 'single finger,Three-finger'

Multi-channel connection

- When connecting the first device, first press Fn+ 1 and then press Fn+C to start the connection.
- Before connecting the second device, press Fn+ 2 once, then press Fn+C to start the connection.
- Before connecting the third device, press Fn+ 3 once, then press Fn+C to start the connection.
- To use multiple devices at the same time, press Fn + 1 / 2 / 3 to switch to the connected devices freely .

Troubleshooting

Please contact the after-sales service.

Copyright

It is forbidden to reproduce any part of this manual without the permission of seller.

Safety instructions

Do not open or repair this device. Do not use the device in a damp environment. Clean the device with a dry cloth.

Warranty

The device is provided with one-year limited hardware warranty from the purchase day.

Keyboard Maintenance

1.Please keep the keyboard away from liquid or humid environment,sauna, swimming pool, steam room and don't let the keyboard get wet in the rain.

2.Please don't expose the keyboard at too high or too low temperature condition.

3.Please don't put keyboard under sun for a long time.

4.Please don't put keyboard close to the flame, such as cooking stoves,candles or fireplace.

5. Avoid sharp objects scratching products, timely to recharge products to ensure the normal use.

FAQ

1.The tablet PC can't connect the BT keyboard?

1: At first check the BT keyboard is into match code state, then open the table PC Bluetooth searching.

2: Checking the BT keyboard Battery is enough, the battery low is also lead to can't connect, you need charge.

2.The battery indication light always flashing when use?

Keyboard indication light always flashing when use, is means the keyboard will be no power ,please charge the power as soon as possible.

3.The table PC display BT keyboard is disconnect?

The Bluetooth keyboard is not used for a period of time, the device will automatically enter the sleep state in order to save power. Press any key on the keyboard to wake up, and the Bluetooth connection will be automatically restored.

Warranty Card

User information

Company or personage full name _____

Contact address _____

TEL _____ Zip _____

The purchased product name and model NO. _____

Purchased date _____

This warranty card only covers hardware and damages in the warranty period caused by normal use. Damage caused by improper operation or any unauthorized maintenance, disassembly or repair does not

Warranty operation is suspended, without the product being sent back to the manufacturer for inspection and confirmation.

If it is not convenient, you can upload photos/videos as proof, and the company's quality staff will contact you and inform you of the