

Outlet Extender with USB Ports and Nightlight

Specifications:

- Model No.: PS-827EU/PS-827US
- AC Input: 200-240V~50Hz (PS-827EU)
100-120V~60Hz (PS-827US)
- AC Output: 200-240V/16A Max, 3680W (PS-827EU)
100-120V/15A Max, 1500W (PS-827US)
- USB-C Output: PD 20W, 5V ≡ 3A, 9V ≡ 2.22A, 12V ≡ 1.67A
- USB-A Output: QC 3.0 18W, 5V ≡ 3A, 9V ≡ 2A, 12V ≡ 1.5A
- USB-C + USB-A Output: 5V ≡ 3A
- Night light: 2W Max
- Total Output: 20W Max
- Material: Fireproof PC
- Size: L108*W60*H78mm
- Motion Sensor Distance: 3M/60°
- When the nightlight switch is on (at lower side), the nightlight turns on by default. In [daytime] or [at darkness without motion detected], the night light turns off automatically after 10 minutes.
- When motion is detected at darkness within the sensing range of 3 meters, the nightlight turns on automatically, but if no motion is detected after 10 minutes, it turns off automatically.
- Slide the switch to adjust the brightness or turn off the night light.
- Use Only Indoors and in Dry Locations.

FC CE

