KCodes 601n

USB DEVICE SERVER

Print, Scan, and Fax over Network Share Multifunction Printer, Scanner, and FaxInstall Multifunction Printer Driver without Connecting the Multifunction Printer to the PC Access Multifunction Printer's Memory Slots over Network Access Digital Camera over Network iTunes Syncs with iPhone and iPod over Network Play Back Music to Remote Speakers Share Hard Drives over Network



7 | XP | VISTA | 2000 | SERVER 2000 | SERVER 2003

Tiger 10.4 | Leopard 10.5 | Snow Leopard 10.6

Languages

EN 繁

RoHS CE FC

1 Functions
- 1.1 Plug and Play Installation
- 1.2 Access USB Devices over Network. Mobiles users no longer need to go through the hassles of connecting USB devices' cables
- 1.3 Print and Obtain Printer Status, Scan, and Fax over Network. Share Multifunction Printer, Scanner, and Fax
- 1.4 Install Multifunction Printer Driver without Connecting the Multifunction Printer to the PC
- 1.5 Access Multifunction Printer' s Memory Slots over Network
- 1.6 Share USB Storage over Network
- 1.7 Access Digital Camera over Network
- 1.8 Sync iTunes with iPhone and iPod over Network
- 1.9 Play Back Music to Remote Speakers



2 Hardware Specification
- 2.1 Wireless LAN
- 2.1.1 IEEE 802.11n 1T1R
- 2.1.2 Wi-Fi Protected Setup
- 2.1.3 Ad-Hoc Mode and Infrastructure Mode
- 2.1.4 WEP (64/128), WPA-PSA (TKIP/AES), and WPA2-PSK (AES)
- 2.1.5 External Antenna
- 2.2 LAN: 10-BaseT and 100Base-TX RJ-45
- 2.3 1 USB Port: USB 2.0 Hi-Speed Type-A
- 2.4 Power Switch: On and Off
- 2.5 Init Button
- 2.6 DC Jack: DC12V
- 2.7 LED Indicators: Power, WLAN, LAN, USB
- 2.8 Microprocessor: Ralink RT3350 MIPS 320MHz
- 2.9 Non-Volatile Memory: 2MBytes
- 2.10 Dynamic Random Access Memory: 16Mbytes
- 2.11 Dimensions: W:78mm(86mm with Antenna)×D:57mm×H:20mm W:59.8g
- 2.12 Operating Temperature and Humidity: 5℃~40℃, 0%-70%

3 Software Specification
- 3.1 Network Protocols: IPv4 TCP/IP
- 3.2 Configuration: TFTP, DHCP, UPnP, HTTP, Remote Firmware Upgrade, Restart, Reset Factory Default
- 3.3 FAT32, FTP Server, and Unicode SMB/CIFS Server
- 3.4 USB Hub Extension Supported
- 3.5 Maximum USB Devices Supported: 127
- 3.6 Supported USB Devices: Multifunction Printer, Scanner, Fax, Multifunction Printer, Hard Drive, iPhone, iPod, USB Digital TV Tuner
- 3.7 Web Server Supports English and Japanese
- 3.8 PC Utility Supports
  - 3.8.1 Windows 2000, Windows XP, Windows Vista, Windows 7, Windows Server 2000, and Windows Server 2003
  - 3.8.2 MacOS X 10.4 Tiger, MacOS X 10.5 Leopard, and MacOS X 10.6 Snow Leopard
  - 3.8.3 English and Japanese

4 Package Contents
- 4.1 KCodes USB Device Server 601n
- 4.2 AC Adaptor: Input AC100V~240V 50/60Hz 1.5A, Output DC12V
- 4.3 CD ROM
- 4.4 Quick Installation Guide
- 4.5 Giftbox

ISO 9001 SGS

Address: 2F, No 501, Sec 2, Tiding Blvd, Neihu District, Taipei 114, Taiwan
Tel: (O) +886-2-2656-2386
Fax: (F) +886-2-2797-6047
Product: sales@kcodes.com
Support: sales@kcodes.com

KCodes