

| | | |
|------------------------|-------------------------------------|--|
| System | Working voltage | DC 9V~17V |
| | Working current | 1.0 ~ 10A |
| | Working temperature | -20°C ~60°C |
| | Storage temperature | -30°C ~80°C |
| | Memory current | <5 mA |
| | Max current antenna output | 500mA |
| | Display | VA colorful or black/white |
| | Clock | yes |
| | Clock setting | yes |
| Radio | Wave Band | FM or Am |
| | FM Frequency Range | 87.5MHz~108MHz |
| | FM IC only | 8035 or Am+FM or Am+FM+RDS for your choice |
| | Storage quantity: | FM radio :18 channels; Am: 12 channels |
| | Search method: | Automatic/Manual |
| | District Setting | europe/America or other districts |
| | RDS (TA, AF, PTY): | per your request |
| Amplifier | Testing voltage: | 14.4V |
| | Nominal RMS output power (W) | 4X35W |
| | Max RMS output power (W) | 4X25W |
| | Amplifier IC: | TDA-7388 |
| | Subwoofer Output | yes |
| | Speaker impedance: | 4Ω |
| Audio | Output: | 4 + 2 subwoofer output or 4 per your request |
| | Support Audio format: | MP3、WMA、WAV、APE、FLAC , ID3.... |
| | Range Volume: | 0~40 |
| | Bass | yes |
| | Treble | yes |
| | Fader/Balance | yes |
| | Pre-set Equalization | Pop/Rock/Classic |
| Bluetooth | Bluetooth spec./version | 5.1 verion |
| | A2DP: | yes |
| | Microphone: | Inter mic |
| | Received Call: | yes |
| | Dialled Call: | yes |
| | Auto Reconnect: | yes |
| Storage Media | SD Card Slot: | yes |
| | USB Port: | yes |
| | SD Card/USB support capacity: | 64GB |
| Other Functions | Remote control: | YES |
| | Pioneer SWC values or cutomized SWC | Yes, can do, but need extra cost |
| | Wireless Bluetooth control APP | Yes |
| | ISO socket | Yes |
| | 2.1A fast charging | Yes, can do, but need extra cost |
| | 7 color button backlights | Yes, can do, but need extra cost |