

## I-Watch Bluetooth



## **User Guide**

### **1. Product Description**

I-watch BT is a new Bluetooth mono headset. It delivers clear voice transmission and high quality sound. With a spare battery, solve the problems of ordinary BT headset short time communication. It makes your hands-free and calls vibration reminding. I-watch BT is stylish and lightweight for all-day comfortable use.

## 2. Product Overview

- 1). Charging USB socket
- 2). Multi-function button (MFB)
- 3). LED indicator
- 4). Main microphone
- 5). Time adjust button
- 6). Power display
- 7). Calls vibration

### What's in the box:

- A. I-watch BT
- B. USB charging cable
- C. Sponge ear bud
- D. User manual



## 3. Charging

User can charge the unit by using a USB cable via a PC.

- 1). Before use, please charge the device for 3 hours to make sure the headset is fully charged and the battery reaches its full capacity.
- 2). Afterwards, each charge cycle may take up to 2 hours.
- 3). Charging for BT  
For Bluetooth: LED indicator will indicate red during charging and turn to blue when charging is complete.
- 4). Charging for Watch Base
  - A. Both the power display and call vibration reminder will flash and reset when charging.
  - B. The character of the battery on the display corresponds to the charging process
  - C. No vibration reminder if the symbol on the indicator disappeared because of low power.
  - D. The watch base automatically charge the Bluetooth headset
- 5). We suggest fully charging the device at least once every **24 hours**.

Note: When the battery power is low, the battery display on LED will flash, please recharge the battery as advised above.

#### **4. Pairing / Connect (Tutorial online)**

- 1). It is important to pair the headset with your Bluetooth device for first time use.
- 2). Pairing procedure:
  - A. Ensure the headset is off.
  - B. Press and hold the multi-function button for about 5 seconds until LED blinks blue and red alternately – you will hear a beep.
  - C. Search the device from your phone / PC.
  - D. Once the "i-Watch BT" is found, click "i-Watch BT" **automatic connect or** follow the steps and enter pin code 0000 to pair.
  - E. Connect the headset to the device.
  - F. Headset is ready for use now.
- 3). Once paired and connected, the headset will automatically connect to your phone whenever you turn the headset on again, provided it is in range.
- 4). The headset will automatically switch itself off if disconnected for 10 minutes.

Note: We found most problems are caused by improper pairing between the headset and the Bluetooth device. Please follow the online tutorial step-by-step.

## **5. Basic Operations**

### **5.1 Headset on/off**

**Turn on** – Press and hold the MFB for 3 seconds until blue LED flashes 3 times and you hear an audible beep.

**Turn off** – Press and hold the MFB for 5 seconds until red LED flashes twice and you hear an audible beep.

NOTE: Under standby mode, the LED indicator will flash blue every 3 seconds.

### **5.2 Answer a call** – Press MFB briefly to answer the call when call vibration reminder.

### **5.3 Reject a call** – Press and hold MFB for 3 times until you hear a beep.

### **5.4 Re-dial** – Briefly press the MFB button twice.

### **5.5 End a call** – Briefly press the MFB once.

### **5.6 Voice dialing**

Please check if your mobile phone supports a voice dialing function.

If your phone does support this function, follow your mobile phone manual instructions to set it up.

1). Press the MFB briefly, then you can hear a short beep.

- 2). Say the name of person you wish to call.
- 3). If the voice tags are paired to the related phone number stored in your mobile phone, the number will be dialed.

#### **5.7 Time adjustment**

- 1) Ensure the LED turned off, press “▲” till LED screen light. The LED will turn off after 8 seconds and press “▲” for time showing.
- 2) Press “▲” till Minutes subtitle flashes.
- 3) Time up: Quickly press “▲” to increase the time.
- 4) Time down: Quickly press “▼” to decrease the time.
- 5) Finally, long press and hold on the ▲ button, clock display back to normal.
- 6) The adjustment of the point in time is same as minute.  
Note: When the watch base no power for a long time, the clock will automatically reset.

#### **5.8 Call vibration reminding**

i-watch BT will vibrate when call coming

## **6. Advanced Operations – Multipoint (Tutorial online)**

- 6.1 No radiation communication via the i-watch BT.
- 6.2 With call vibration reminding, solve the problems when your BT devices away from you.
- 6.3 Bluetooth headset is placed on the watch base is very convenient.
- 6.4 With a spare battery of the watch base, solve the problems of ordinary Bluetooth headsets short time.

## **7. Product Specification**

- \* Bluetooth compliance: Bluetooth 3.0
  - \* Support profiles: HSP, HFP and A2DP profile
  - \* Stand-by time: up to 200 hours
  - \* Talk time: up to 1.5 hours
  - \* Battery charging Time: about 2 hours
  - \* Charger voltage: DC5.0V 300~500mA
  - \* Weight: 48.0g
  - \* Package: OEM or I-watch BT Standard Packing
- Note: The talk and standby times may vary when used with different mobile or other compatible BT devices, usage settings & styles and environments.



## 8. Wearing Instruction Demo

