



2000W TO 3000W DC TO AC POWER INVERTER

| Model | USD | Picture | Weight | Size (MM) | Product Specification |
|------------------------|-----|---|--------|-------------|---|
| 2000-(power inverter) | 106 |  | 3.5KG | 310*150*70 | 1.Continuous power:2000W ; |
| | | | | | 2.Surge power::4000W; |
| | | | | | 3.Input volt: 12V/24V/48V/110VDC |
| | | | | | 4.Output volt:100V/110V/120V/220V/230V/240VAC; |
| | | | | | 5.Frequency:50±1HZ ; |
| | | | | | 6.Efficiency:>86% |
| | | | | | 7.No load current drsws:<0.6A |
| | | | | | 8.THD:<5% |
| | | | | | 9.Dimension(mm):310*150*70;Weight:3.5KG±0.2KG |
| | | | | | 10. Inside box(mm):390*190*110;Weight:6.1±0.2KG |
| | | | | | 11. Outside box(mm):420*405*265;Weight:14.5±0.2KG |
| | | | | | 12.Qty /box:4 pcs |
| 3000(power inverter) | 174 |  | 7.2KG | 340*150*152 | 1.Continuous power:3000W ; |
| | | | | | 2.Surge power::5000W; |
| | | | | | 3.Input volt: 12V/24V/48V/110VDC |
| | | | | | 4.Output volt:100V/110V/120V/220V/230V/240VAC; |
| | | | | | 5.Frequency:50±1HZ ; |
| | | | | | 6.Efficiency:>86% |
| | | | | | 7.No load current drsws:<0.6A |
| | | | | | 8.THD:<5% |
| | | | | | 9.Dimension(mm):340*150*152;Weight:7.2KG±0.2KG |
| | | | | | 10. Inside box(mm):485*190*190;Weight:7.8±0.2KG |
| | | | | | 11. Outside box(mm):510*410*225;Weight:14.5±0.2KG |
| | | | | | 12.Qty /box:2 pcs |

**1.MOQ: 100W-500W
(500piece) 800W-3000W
(300piece)**

**2.Delivery time:20days after
confirm the deposit**

**3.Expiry date:30days after the
date of offer**

**4.Payment:T/T,30% as
deposit,balance must be paid
before shipment**