



SHENZHEN KINGSAKO ELECTRONICS CO., LTD

5-6F, C Building, He-Xi, Huanggangling Industrial, Xixiang, Baoan, Shenzhen, CHINA
 Tel: 0086-755-61153288 mail:szsako@sako.com.cn skype:szsakopower Web:
 www.kingsako.com

SAKO PUMPS



SAKO PUMPS SERIES MAIN FUNCTION

- Can power by AC supply, and used for solar pumps;
- Wide lift reach to 400ms;
- Can be portable and scalable;
- Very low operation/ maintenance;
- Acceptable capital costs & low recurrent costs;
- Remote applications;
- Relatively easy to install;



OHSMS 28001 ISO 9001:2000 ISO 14001:2004



3" Deep Well Pump

Outlet: G1-1

1-phase AC Supply, 220-240V / 50Hz	Motor power		L/min	0	8	17	25	30	33	42	47
	KW	Hp		m³h	0	0.5	1	1.5	1.8	2	2.5
75DS10-0.25	0.25	0.33	Head (m)	38	36	33	28	23	20	10	4
75DS15-0.37	0.37	0.5		55	54	50	40	34	29	14	5
75DS22-0.55	0.55	0.75		79	78	72	58	50	42	20	7
75DS30-0.75	0.75	1		108	105	93	76	64	57	27	10
75DS40-1.1	1.1	1.5		144	132	120	91	76	60	25	13

3.5" Deep Well Pump

Outlet: G1-1

4SPS09-0.37	4SPT09-0.37	0.37	0.5	Head (m)	55	51	45	35	25	14
4SPS13-0.55	4SPT13-0.55	0.55	0.75		80	73	64	51	36	21
4SPS18-0.75	4SPT18-0.75	1.75	1		110	101	89	72	50	29
4SPS23-1.1	4SPT23-1.1	1.1	1.5		141	129	114	91	64	37
4SPS28-1.5	4SPT28-1.5	1.5	2		171	157	139	110	78	45
4SPS33-1.5	4SPT33-1.5	1.5	2		202	186	163	131	92	53
4SPS40-2.2	4SPT40-2.2	2.2	3		245	225	198	150	112	65
4SPS48-2.2	4SPT48-2.2	2.2	3		294	270	237	185	134	78
—	4SPT55-3	3	4		336	309	272	218	154	89
—	4SPT65-4	4	5.5		398	365	321	255	182	105

6" Stainless Steel Deep Well Pumps

Outlet: G3"

3-phase AC Supply, 380-415V / 50Hz	Motor power		L/min	0	167	233	283	333	367
	KW	Hp	m ³ /h	0	10	14	17	20	22
6SPT07-4	4	4	Head (m)	75	69	61	56	49	33
6SPT09-5.5	5.5	5.5		97	81	79	72	63	43
6SPT12-7.5	7.5	7.5		129	108	105	96	84	57
6SPT15-9.2	9.2	9.2		162	134	132	120	105	72
6SPT18-11	11	11		194	161	158	144	126	86
6SPT21-13	13	13		226	188	184	168	147	100
6SPT24-15	15	15		259	215	211	192	168	115
6SPT30-18.5	18.5	18.5		323	297	263	240	210	143