



Shenzhen Yu Senda Electronics Co., Ltd.

Address: Second Floor of Third Building, Wanyan Industrial City, Qiaotou Community, Fuyong Street, Bao'an District, Shenzhen, Guangdong,

Mobile/Wechat/Skype: +86 147-7615-3143 Becky Shen Email: sales4@sztzhdz.com QQ: 2395531390

YSD8808 2.0CH Soundbar

Model: YSD8808



Parameter

Features

1, Audio Output: 2.0CH,
2, AUX input / OPTICAL input
3, USB input, HDMI ARC output
4, Wireless Bluetooth connection
5, LED display
6, Plastic case, Digital Amplifier with DSP inside
7, Remote controller

Power Supply

AC 110V-240V power supply

Power output

15W*4=60W R.M.S.

Driver Unit

2.25"*4, 4Ω

Frequency Response

45Hz-20KHz

S/N

≥ 72dB

	Distortion	<=1%(1K/1W)
	Input Sensitivity	800mV+50mV /1KHz
	Bluetooth Version	Version: 5.0
	Accessories:	Line-in cable, AC cable, User manual, Remote control
Shipping info	Product size:	920*83*66 mm
	Colorbox size:	956*107*136 mm
	Carton size:	966*287*345 mm/0.09564
	QTY/CTN	6 pcs
	N.W./G.W.:	15 / 16 kgs
	20GP:	1756 pcs
	40GP:	3510 pcs
	40HQ:	4140 pcs