



Shenzhen Yu Senda Electronics Co., Ltd.

Address: Second Floor of Third Building, Wanyan Industrial City, Qiaotou Community, Fuyong Street, Bao'an District, Shenzhen, Guangdong, China

Mobile/Wechat/Skype: +86 147-7615-3143 Becky Shen Email:sales4@sztzhdz.com QQ: 2395531390

Quotation

YSD8809 2.0CH Soundbar

Model: YSD8809



Parameter

Features

1, Audio Output: 2.0CH,
2, AUX input /OPTICAL input
3, USB input, HDMI ARC output
4, Wireless Bluetooth connection
5, LED display
6, Plastic case, Digital Amplifier with DSP inside
7, Remote control

Power Supply

SMPS 110V-240V ~ 50/60Hz DC 24V

Power output

15W*4=60W R.M.S.

Driver Unit

2"*4, 4Ω

Frequency Response

45Hz-20KHz

S/N

≥ 72dB

	Distortion	<=1%(1K/1W)
	Input Sensitivity	800mV+50mV /1KHz
	Bluetooth Version	Version: 5.0
	Accessories:	Line-in cable, AC cable, User manual, Remote control
Shipping info	Product size:	900*67*60 mm
	Colorbox size:	945*136*107 mm
	Carton size:	955*287*345 mm/0.0946
	QTY/CTN	6 pcs
	N.W./G.W.:	14.4 / 15.4 kgs
	20GP:	1776 pcs
	40GP:	3552 pcs
	40HQ:	4140 pcs