



www.meeGo.cn

MeeGoDock V10 13.3inch yoga style



Specification

General	
Style	13.3inch laptop style 360degree turn over case with touch screen for USB-C mobile phone&HDMI Device
Main Function	
1. Connect mobile phone usb c3.1 port through USB C and make mobile phone a PC	
2. Connect Mini PC/Stick PC/Develop Board to HD&MI port and make it a complete PC	
3. Connect Macbook from USB C port to make 10 a second display	
4. Wireless connection for type c phone is optional.	
5. MeeGo Dock V10B can use as power bank to charge mobile phone.	
6. Expand mobile phone storage on laptop Micro SD Card Slot, support Max 256GB	
7. Support adjust brightness, volume level, Audio/Vido play/suspend/back/forward, charging, full charged, etc same as notebook.	
Screen	
Touch Screen	Support Multi-touch
Display	13.3 inch 1920*1080
Keyboard	
Keyboard	full size, backlight
Wireless	
WiFi	Miracast optional
Touch Pad	
Touch Pad	Mouse track
Battery	
7.6V 6300MAH	4pcs 3.7V 3150MAH cell, or 2PCS 3.7V 6300MAH Cell
Speaker	
Speaker	Built-in stereo speakers 8Ω
Mic	
Mic	Built in
I/O	
DC *1	DC In, 12V/3A
HD&MI*1	HD&MI IN
USB C*1	5V/3A Power& Data &Video and Audio input for mobile phone/stick pc/mini pc/development board
USB2.0 A*1	Data transfer, Maximum power output up to 5V/500mAh
Audio Jack*1	3.5mm stereo mini jack
Micro SD Cardreader*1	Support up to 256GB
Device supporting	
Sam&sung S8/S8+/S9/S9+and above	Supporting DEX desktop function
Hua&wei MATE10/Mate20/P20&	Supporting desktop function
MAC&BOOK	Supporting all models with Type C
	Supporting all devices with USB3.1 type C port or HD&MI port (NOTEBOOK, TABLET , MINI PC,MOBILE PHONE, ALL IN ONE, DEVELOPMENT BOARD)
Power Spec	
Power Adapter	PD61W
Physical Spec	
Dimension	332*215.4*14.9mm
Weight	1.5KG
Material	Aluminium Alloy
Color	Black,Gary,Silver,Gold
Working Temperature	0-40°C
Storage Temperature	-(20)-70°C
Package	
Package	1*V10B, 1* Gift Box, 1*power adapter with cable, 1*USB C 3.1 cable

Remark: If customer want charge to PD charger, we can modify case and modify PCBA.
Remark: Wireless dex optional, Miracast optional