

Model	Voltage	No Load		At Maximum Efficiency				Stall	
		Current	Speed	CUrrent	Speed	Torque	Output	Current	Torque
	V	A	RPM	A	RPM	g.cm	W	A	g.cm
FF-180PA-17124V	3.7	0.06	5000	0.22	4300	10	0.6	1	70
FF-180SH-2568V	3	0.16	7500	0.7	6000	20	1.6	2.8	130
FD-180SH-19100V	12	0.18	18000	0.56	16700	20	6.3	4.3	240