



Shenzhen Yu Senda Electronics Co., Ltd.

Address: Second Floor of Third Building, Wanyan Industrial City, Qiaotou Community, Fuyong Street, Bao'an District, Shenzhen, Guangdong, China

Mobile/Wechat/Skype: +86 147-7615-3143 Becky Shen Email: sales4@sztzhdz.com QQ: 2395531390

YSD8806 2.0CH Soundbar

Model: YSD8806



Parameter

Features	1, Audio Output: 2.0CH, 2, AUX input / OPTICAL input 3, USB input, HDMI ARC output 4, Wireless Bluetooth connection 5, LED display 6, Plastic case, Digital Amplifier with DSP inside 7, Remote controller
Power Supply	SMPS 110V-240V ~ 50/60Hz DC 18V 2.5A
Power output	15W*4=60W R.M.S.
Driver Unit	2"*4, 4Ω
Frequency Response	45Hz-20KHz
S/N	≥ 72dB
Distortion	≤ 1% (1K/1W)

	Input Sensitivity	800mV+50mV /1KHz
	Bluetooth Version	Version: 5.0
	Accessories:	Line-in cable, DC adapter, User manual, Remote control
Shipping info	Product size:	900*83*63 mm
	Colorbox size:	1008*136*107 mm
	Carton size:	1024*287*370 mm/0.1087
	QTY/CTN	6 pcs
	N.W./G.W.:	14.4 / 15.2 kgs
	20GP:	1550 pcs
	40GP:	3090 pcs
	40HQ:	3640 pcs