



Shenzhen Yu Senda Electronics Co., Ltd.

Address: Second Floor of Third Building, Wanyan Industrial City, Qiaotou Community, Fuyong Street, Bao'an District, Shenzhen, Guangdong, China

Mobile/Wechat/Skype: +86 147-7615-3143 Becky Shen Email: sales4@sztzhdz.com QQ: 2395531390

YSD8807 2.0CH Soundbar 60W

Model: YSD8807



Parameter

Features

1, Audio Output: 2.0CH,
2, AUX input / OPTICAL input
3, USB input, HDMI ARC output
4, Wireless Bluetooth connection
5, LED display
6, Plastic case, Digital Amplifier with DSP inside
7, Remote controller

Power Supply

SMPS 110V-240V ~ 50/60Hz DC 24V

Power output

15W*4=60W R.M.S.

Driver Unit

2"*4, 4Ω

Frequency Response

45Hz-20KHz

S/N

≥ 72dB

Distortion

≤ 1% (1K/1W)

	Input Sensitivity	800mV+50mV /1KHz
	Bluetooth Version	Version: 5.0
	Accessories:	Line-in cable, DC adapter, User manual, Remote control
Shipping info	Product size:	900*60*60 mm
	Colorbox size:	1008*136*107 mm
	Carton size:	1024*287*345 mm/0.1014
	QTY/CTN	6 pcs
	N.W./G.W.:	14.4 / 15.2 kgs
	20GP:	1656 pcs
	40GP:	3312 pcs
	40HQ:	3900 pcs