

Outlet Extender

with Wireless Charging, USB Ports and Night Light

Specifications:

- Model No.: PS-656UK
- AC Input: 200-240V~50Hz
- AC Output*2: 250V/13A Max, 3250W
- Wireless Output: 5W/7.5W/10W/15W
- USB-C Output: PD 20W, 5V = 3A, 9V = 2.22A, 12V = 1.67A
- USB-A Output: QC3.0 18W, 5V = 3A, 9V = 2A, 12V = 1.5A
- USB-C + USB-A Output: 15W Max
- Night Light: 2W Max
- Total DC Output: 32W Max
- Material: Fire-resistance PC
- Size: L150*W90*H51mm
- Motion Sensor Distance: 3M / 60°
- Use Only Indoors and in Dry Locations.
- When the nightlight switch is on (at lower side), the nightlight turns on by default. In [daytime] or [at darkness without motion detected], the nightlight turns off automatically after 10 minutes.
- When motion is detected at darkness within the sensing range of 3 meters, the nightlight turns on automatically, but if no motion is detected after 10 minutes, it turns off automatically.
- Slide the switch to adjust the brightness or turn off the night light.

