

- [Wide Applications]Digital Multi Tester with High Accuracy measure DC AC voltage, DC current, resistance, temperature($^{\circ}\text{F}$), battery test, positive diode voltage fall and audible continuity.This advanced tester can diagnose automotive, industrial and household electrical issue.
- [NCV Detection and Buzzer LED]The Digital Multi Tester have Non Contact AC Voltage (NCV) detection area.And The LED will light up when the built-in buzzer sounds.
- [Easy to Read]Convenient features like Data Hold, Large LCD Backlit Screen can ensures easy use in dimly lit places. And it has relative value measurement, data retention...
- [Push Button Operation]Push button design for easy single-hand operation, can quickly change function with one hand .All button (no switch) operation allows you to maintain contact with a probe while selecting the function you want.

Product Specifcaiton:

Model HP-42SMART

AC Current 0.3mA/60mA/600mA/6A/10A

AC Voltage 0.5V/6V/60V/600V

Measuring Resistance Range 6k Ω /60k Ω /600k Ω /6M Ω /60M Ω

Operating Mode Auto range / Manual range control

DC Current 0.3mA/60mA/600mA/30mA/6A/10A

DC Voltage 0.5V/6V/60V/600V

Measuring Capacitance Range 60nF/600nF/6 μF /60 μF /600 μF /6mF/60mF

Display 6000 Counts

Product Function:

Diode Test YES

Continuity Buzzer YES

Data Hold YES

Back Light YES

Auto Power Off YES

True RMS YES

NCV YES

General Features:

Battery Type:1.5V(AAA)*2

Dimension:150*76*33mm

Weight:220g