



<b>CPU</b>	<b>Amlogic S905X3 Quad Core ARM Cortex A55 @2GHz</b>	
<b>GPU</b>	G31TM MP2 GPU processor	
<b>ROM</b>	DDR3: <b>2G/4GB</b>	
<b>Ram</b>	EMMC : <b>16G/32GB</b>	
<b>WiFi</b>	<b>2.4 G、 2.4G+ 5.8G WiFi with BT4.1, 1000Mbps</b>	
<b>Bluetooth</b>	Support	
<b>I/O</b>	1*HDMI	HDMI 2.1 ,Support HDMI CEC, Dynamic HDR and HDCP 2.2,4Kx2K@75 max resolution output.
	1*AV OUT	480i/576i standard definition output
	2*USB	1*USB 2.0, 1*USB 3.0
	1*RJ45	Ethernet Interface;Support 10/100Mbps
	1*TF CARD	Support 4GB/8GB/16GB/32GB
	1*DC	5V/2A
<b>Power</b>	DC 5V/2A ; LED indicator , Working : Blue;	
<b>Software</b>		
<b>OS</b>	Android 9.0	
<b>Video</b>	<p>Amlogic Video Engine (AVE) with dedicated hardware decoders and encoders Support multi-video decoder up to 4Kx2K@60fps+1x1080P@60fps  Supports multiple “secured” video decoding sessions and simultaneous decoding and encoding  Video/Picture Decoding</p> <ul style="list-style-type: none"> <li>- VP9 Profile-2 up to 4Kx2K@60fps</li> <li>- H.265 HEVC MP-10@L5.1 up to 4Kx2K@60fps</li> <li>- AVS2-P2 Profile up to 4Kx2K@60fps</li> <li>- H.264 AVC HP@L5.1 up to 4Kx2K@30fps</li> <li>- H.264 MVC up to 1080P@60fps</li> <li>- MPEG-4 ASP@L5 up to 1080P@60fps (ISO-14496)</li> <li>- WMV/VC-1 SP/MP/AP up to 1080P@60fps</li> <li>- AVS-P16(AVS+) /AVS-P2 JiZhun Profile up to 1080P@60fps</li> <li>- MPEG-2 MP/HL up to 1080P@60fps (ISO-13818)</li> <li>- MPEG-1 MP/HL up to 1080P@60fps (ISO-11172)</li> <li>- RealVideo 8/9/10 up to 1080P@60fps</li> <li>- Multiple language and multiple format sub-title video support</li> <li>- MJPEG and JPEG unlimited pixel resolution decoding (ISO/IEC-10918)</li> <li>- Supports JPEG thumbnail, scaling, rotation and transition effects</li> <li>- Supports *.mkv,*.wmv,*.mpg, *.mpeg, *.dat, *.avi, *.mov, *.iso, *.mp4, *.rm and *.jpg file formats</li> </ul>	
<b>Audio</b>	<p>Supports MP3, AAC, WMA, RM, FLAC, Ogg and programmable with 7.1/5.1 down-mixing Built-in serial digital audio SPDIF/IEC958 input/output and PCM input/output  built-in TDM/PCM/I2S ports with TDM/PCM mode up to 384kHz x32bits x 8ch or 96kHz x 32bits x 32ch and I2S mode up to 384kHz x 32bits x 8ch  Digital microphone PDM input with programmable CIC, LPF &amp; HPF, support up to 8 DMICs Built-in stereo audio DAC  Supports concurrent dual audio stereo channel output with combination of analog+PCM or I2S+PCM</p>	
<b>Image</b>	HD JPEG、 BMP、 GIF、 PNG、 TIF	
<b>Language</b>	English French German Spanish Italian etc multilateral languages	

<b>Appliactions</b>	
<b>Online</b>	Browse all video websites,support Netflix,Hulu,Flixster, Youtube, etc.
<b>Apps</b>	Apps download freely form android market、 amazon app store etc.
<b>Medium</b>	Local Media playback,Support HDD, U Disk ,TF Card .
<b>Talk online</b>	Support SKYPE video call ,MSN , facebook ,twitter ,QQ etc
<b>Others</b>	Support Email,office suit etc.
<b>Accessories :</b>	
1、 HDMI cable *1	
2、 IR Remote *1	
3、 User Manual *1	
4、 Package box *1	
5、 Power adapter *1	