

Model	Voltage	No Load		At Maximum Efficiency				Stall	
		Current	Speed	CUrrrent	Speed	Torque	Output	Current	Torque
	V	A	RPM	A	RPM	g.cm	W	A	g.cm
FF-120PA-1581V	3.7	0.09	6500	0.25	5600	10	0.9	0.89	70
FF-120PA-3120	1.2	0.35	8600	1.82	5500	20	1.1	4	70
FF-120PA-1950V	3	0.16	9000	0.45	7600	10	1.1	2	70