

Smart Plug Specification



Basic Information	
Product Series	IN02 JX09B
Standby Power	<0.5W
Voltage	100V - 250VAC 50Hz/60Hz
Maximum load current	16A
Max. Load	3840W
Security Mechanism	WAP/WAP2
Encryption type	WEP/TKIP/AES

Wireless Standard	WIFI 2. 4GHz IEEE 802. 11 b/g/n
App	Smart Life/Tuya Smart
Dimension	80*45MM
Box Size	55*55*88MM
Gross Weight	0.1kgs
Casing Material	PCVO
Operating systems	IOS
Applicable Place	Indoor
Working Temperature	0℃~60℃(32°F~104°F)
Certification	CE, RoHs, FCC, ETL, UL

Features & Functions

- WiFi direct connection to internet, easy to use
- Timely monitor and control all electrical appliances at home from long distance
- Remote control on Smartlife App via 3G/4G/WiFi
- Works with Amazon Alexa/Google Home/IFTTT
- Support the energy monitor , overload protection
- Timing control switch function
- Scene function for automation control
- Real-time status displays on App
- Share function with family members
- Cycle through/off status by clicking the switch button on the socket

Application

WORKS WITH ALEXA AND GOOGLE HOME

Works with Amazon Alexa and Google Home for hands-free voice control.



Remote Control with Smart Life App

Simply use the Smart Life App
your smart phone or tablet to control your devices



Work with **Amazon Alexa** **Google Assistant**



"Hi Google, turn off the light"



Hi, Alexa, make a coffee for me.

Simply use your

voice to
control





WiFi Smart Plug

Mini Smart Wi-Fi Switch

Make Your Life Better



Wi-Fi remote control your devices

Timing/Countdown Schedule Function

Alexa Echo Voice Control

For your AC, Microwave, Geyser, Washing Machine

Electricity Power Energy Saving



Wifi
Connect



Safety
Button



Timing
Switch



Energy
Monitor



Voice
Control



Remote
Control

Remote Control with Smart Life App

Simply use the Smart Life App
your smart phone or tablet to control your devices



Connecting Smart Speaker to Realize Voice Control

Wifi socket can work with the smart speaker,
such as Amazon Alexa, Google Home and so on, and realize voice control



Achieving voice control by connecting with intelligent speakers
such as Amazon Alexa, Google Home and Tmall Genie, that's so amazing.



EASY TO SET UP AND INSTALL

Easy set up with free app Smart Life, connect to a 2.4GHz Wi-Fi network. No hub required.



Smart Life



Voice control

Simply give a voice command to Alexa or Google Home to turn on/off switch when your hands are full. and enjoy the comfort of voice.



Operating Steps

A. One-click configuration

1. Please plug the socket into the power supply, wait for the indicator to flash quickly, or press and hold the key for 5 seconds until the indicator flashes quickly (2 times per second).
2. Connect your phone to wifi and confirm success.
3. Open the app, click the icon in the upper right corner of the device list, select "Socket" to enter the configuration device interface.
4. Click "Please confirm that the indicator is flashing", enter the password of the WIFI currently connected to the mobile phone, and click "confirm".
5. Waiting for configuration, after the configuration is successful, click "Finish" to jump to the function interface of the socket.

B.AP Configuration

The AP Configuration is a patching configuration. If the one-click configuration fails, you can use the AP configuration. Methods as below:

1. Press and hold the key 5S for a long time, the indicator light enters the state of slow flashing (lights off for 2 seconds) .

2. Open the app, click the icon in the upper right corner of the device list, select "Socket" to enter the configuration device interface, click on the upper right corner "Compatibility mode" enters the AP configuration interface.
3. Click "Please confirm that the indicator light is flashing slowly", enter the password of the WIFI connected to the current mobile phone, and click "Confirm".
4. Click "Go to Connect", it will jump to the WIFI list interface, select SmartLife-XXXX and click "Connect".
5. Click the back button on the phone to wait for the configuration. After the configuration is successful, click "Finish" to jump to the function interface of the socket.

Warnings and precautions

1. The plug must be fully inserted into the wall socket.
2. Do not use conductors or other tools to insert into the jack.
3. If there is radio frequency interference during operation, the socket may not work.
- 4, can only be used indoors.
5. Please use it in a dry place. Do not use it in a damp place such as a bathroom.
- 6, please ensure that the electricity is safe, the resistive load current can not be higher than 10A.
7. Keep out of reach of children.