



Shenzhen Yehai Sci.& Tech.Deve.Co.,Ltd

Address: Room No.216,Third Floor,Jin Huiqiu Building,Langshan No.2Road,

NorthArea,Science&TechnologyPark,Nanshan Dis

Tel : 86-755-26509606; Fax: 86-755-26502620; Mobile : 86-13699890579

Contact name: Miss Elinor; MSN: elinor201012@msn.cn; Skype: elinor20101

Email: chinayehai@globalsources.com; elinor@yehai.net.cn; jiangchen998@16

Website: <http://www.globalsources.com/chinayehai.co>; <http://www.chinayehai.com>

Measurement Function	Range	Resolution	Accuracy
DC Voltage	6V	1mV	$\pm (0.8\% \text{rdg} + 5 \text{digits})$
	60V	10mV	
	600V	0.1V	
	1000V	1V	$\pm (1\% \text{rdg} + 2 \text{digits})$
AC Voltage	6V/50Hz	1mV	$\pm (1.2\% \text{rdg} + 5 \text{digits})$
	60V/50Hz	10mV	
	600V/50Hz	0.1V	
	700V/50Hz	1V	$\pm (1.2\% \text{rdg} + 5 \text{digits})$
AC Current	600A	0.1A	$\pm (2.5\% \text{rdg} + 5 \text{digits})$
	1000A	1A	$\pm (3.0\% \text{rdg} + 5 \text{digits})$
Resistance	600 Ω	0.1 Ω	$\pm (1\% \text{rdg} + 3 \text{digits})$
	6k Ω	1 Ω	
	60k Ω	10 Ω	
	600k Ω	0.1k Ω	
	6M Ω	1k Ω	
	60M Ω	10k Ω	$\pm (5.0\% \text{rdg} + 5 \text{digits})$